



FIGURE A  
 MAXIMUM OUTPUT CURRENT OF ANY DUAL INPUT VOLTAGE OR VOLTAGE DOUBLER UNIT OPERATED AT LOWER INPUT VOLTAGE.

\* MAXIMUM OUTPUT CURRENT IN OUTPUT VOLTAGE RANGE FROM 0 TO PERCENT ABOVE LINE VOLTAGE. AT HIGHER OUTPUT VOLTAGES, OUTPUT CURRENT MUST BE REDUCED ACCORDING TO RATING CURVE, FIGURE A.

++ MAXIMUM KVA AT MAXIMUM OUTPUT AND CORRESPONDING DE-RATED CURRENT. MAXIMUM KVA AT LOWER OUTPUT VOLTAGES MAY BE CALCULATED FROM RATING CURVE, FIGURE A.

V.D. = VOLTAGE DOUBLER.

SPECIFICATIONS									
WIRING	INPUT		OUTPUT			SHAFT ROTATION TO INCREASE VOLTAGE	TERMINAL CONNECTIONS		
	VOLTS	HERTZ	VOLTS	MAX. AMPS	MAX. KVA		FOR INCREASING VOLTAGE AS VIEWED FROM ROTOR END		
							INPUT	JUMPER	OUTPUT
SINGLE PHASE	240	50/60	0-240	84	20.2	CW	1-4	---	1-D
			0-280	84	23.5	CW	1-2	---	1-D
PARALLEL	120	50/60	0-280	84-36 V.D.	10.2 ±	CW	1-5	---	1-D

  

UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ±	DECIMALS	HOLES	ANGLES	DRAFT	UNITS	TITLE:
.XX	.04	.002	1°	1-1/2°	IN [mm]	SPEC. CONTROL DWG.
MATERIAL:						VARIABLE TRANSFORMER
						TYPE: 5021-3P
DRAWN BY		DATE	FIRST USED ON	DO NOT SCALE DWG.	DRAWN BY	
CHECKER		DATE	WEIGHT APPROX.	CAGE CODE	DRAWN BY	
ENGINEER		DATE	SCALE	SHEET 1 OF 1	DRAWN BY	

